



FISCHER PANDA 30-4 PMS Three-phase Sea Generating Set 1500 rpm 29.4 kVA

Product description:

MARINE GENERATOR FISCHER PANDA 30-4PMS SUPERSILENCED 29.4 KVA

Generator for boats Fischer Panda 30-4PMS three-phase 29.4 KVA with 1500 rpm motor. The Fischer Panda 30-4PMS three-phase marine generator is designed with a soundproof cabin that makes it super-silent. The Fischer Panda 30-4PMS three-phase generator is built with a diesel-powered Mitsubishi engine. The Fischer Panda 30-4PMS three-phase generator alternator is 4-pole with H insulation class. Thanks to its compactness, size and low weight, the Fischer Panda 30-4PMS three-phase marine generator is also suitable to be mounted on boats with little space available.

Fischer Panda 30-4PMS marine generator:

Phase Type: Three-phase
Maximum Output: 25 kW
Continuous Output: 22.5 kW
Maximum Output: 29.4 kVA
Continuous Output: 26.5 kVA
Frequency: 50 Hz
Voltage: 400 V
Engine rpm: 1500 rpm
Displacement: 3331 cc.
Cooling: Water
Sound Cover Type: MPL 4DS
Length: 1280 mm
Width: 740 mm
Height: 830 mm
Dry weight: 720 Kg



Based on the robust and compact Fischer Panda 30-4PMS generator set, these heavy duty (HD) versions run at 1500 rpm and 50 Hz.

The Fischer Panda 30-4PMS marine generator is enclosed in a soundproofed capsule which significantly reduces noise emissions and makes this product super-silent.

The generators are heavier than standard PMS generators. They use a heavy-duty diesel engine and, because they run at 1500 rpm, have a 4-wire coil, which also means that the alternator has a heavier 4-pole construction.

The heavy-duty construction and low rpm results in a durable and quiet generator set.

On our website you can find other marine generators such as the Fischer Panda 30-4PMS with different specifications. Browse the entire catalogue of marine generators to find the one best suited to your needs. On our catalogue you can find a wide range of marine products at the best price.

Images and technical data are not binding.

Product features:

Phase: Three phase

Maximum power three phase (KW): 25

Continuous power three phase (KW): 22.4

Maximum power three phase (KVA): 29.4

Continuous power three phase (KVA): 26.5

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 400

Engine: Mitsubishi S4S

Engine rpm (rpm): 1500

Speed governor: Electronic

Starting system: Electric

Engine capacity (cm³): 3331

Number cylinders: 4

Cooling: Water

Poles: 4

Motor insulation class: H

Length (mm): 1280

Width (mm): 740

Height (mm): 830

Dry weight (Kg): 720

Silenced: Yes

Super silenced: Yes

Product type: Generator

Voltage regulator: Capacitor



Engine manufacturer: Mitsubishi